Constructing Linear Codes with Good Joint Spectra

Speaker: Shengtian Yang Dept. of ISEE Zhejiang University

Motivation

Distributed source coding

- How to design an optimal coding scheme based on linear codes for lossless transmission of arbitrary correlated sources over multiple-access channels? (A Joint Source Channel Coding (JSCC) Problem)
- S. Yang, Y. Chen, and P. Qiu, "Linear codes based lossless joint source channel coding for multiple-access channels," submitted to IEEE Trans. Inf. Theory, draft available at http://arxiv.org/abs/cs.IT/0611146.





$$\Phi_n(v^n) \equiv q_n(v^n, \Sigma_l(F_n(\Sigma_n(v^n))) + U^l) \quad \forall v^n \in \mathcal{V}^n.$$



- Gallager, "Information Theory and Reliable Communication", 1963 (Main Ideas: Coset codes, Quantization mapping)
- Shulman and Feder, "Random coding techniques for nonrandom codes", 1999
- Bennatan and Burshtein, "On the application of LDPC codes to Arbitrary Discrete-Memoryless Channels", 2004

Fixed-length source coding based on linear codes (for comparison)



- Csiszar, "Linear codes for sources and source networks: Error exponents, universal coding", 1982
- Muramatsu, et al, "Low-density paritycheck matrices for coding of correlated sources", 2005
- Yang and Qiu, "On the performance of linear Slepian-Wolf codes for correlated stationary memoryless sources," 2005

Optimality of the scheme

By the code-spectrum approach, we have proved that the proposed scheme can achieve optimal performance if good linear codes (linear codes with good joint spectra) and good conditional probability distributions (determining the design of quantization map) are chosen. (under MAP decoding)

Three open problems

- A problem of optimization. How to find good conditional probability distributions?
- A problem of coding. How to construct good linear codes? (good joint spectra)
- A problem of decoding. How to decode with low complexities and permissible loss of optimality? (MAP decoding are impractical when coding length is large)

Code-spectrum approach and some new results

The code-spectrum approach

- A distribution of distributions (a distribution of types), well established by the method of types.
- A generalized and normalized version of the weight distribution and input-output weight distribution for binary codes.

Definition of spectra

The *type* of a sequence x^n in \mathcal{X}^n is the empirical distribution P_{x^n} on \mathcal{X} defined by

$$P_{x^n}(a) \equiv \frac{1}{n} \sum_{i=1}^n \mathbb{1}\{x_i = a\} \quad \forall a \in \mathcal{X}$$

The spectrum of a nonempty set $A \subseteq \mathcal{X}^n$ is the empirical distribution $S_{\mathcal{X}}(A)$ on $\mathcal{P}(\mathcal{X})$ defined by

$$S_{\mathcal{X}}(A)(P) \equiv \frac{|\{x^n \in A | P_{x^n} = P\}|}{|A|} \quad \forall P \in \mathcal{P}(\mathcal{X}).$$

Analogously, the *joint spectrum* of a nonempty set $B \subseteq \mathcal{X}^n \times \mathcal{Y}^m$ is the empirical distribution $S_{\mathcal{X}\mathcal{Y}}(B)$ on $\mathcal{P}(\mathcal{X}) \times \mathcal{P}(\mathcal{Y})$ defined by

$$S_{\mathcal{XY}}(B)(P,Q) \equiv \frac{|\{(x^n, y^m) \in B | P_{x^n} = P, P_{y^m} = Q\}|}{|B|}$$

for all $P \in \mathcal{P}(\mathcal{X}), Q \in \mathcal{P}(\mathcal{Y})$.

Furthermore, we can define the *marginal spectra* and the *conditional spectra*:

$$S_{\mathcal{X}}(B)(P) \equiv \sum_{Q \in \mathcal{P}(\mathcal{Y})} S_{\mathcal{X}\mathcal{Y}}(B)(P,Q)$$
$$S_{\mathcal{Y}}(B)(Q) \equiv \sum_{P \in \mathcal{P}(\mathcal{X})} S_{\mathcal{X}\mathcal{Y}}(B)(P,Q)$$
$$S_{\mathcal{Y}|\mathcal{X}}(B)(Q|P) \equiv \frac{S_{\mathcal{X}\mathcal{Y}}(B)(P,Q)}{S_{\mathcal{X}}(B)(P)}$$
$$S_{\mathcal{X}|\mathcal{Y}}(B)(P|Q) \equiv \frac{S_{\mathcal{X}\mathcal{Y}}(B)(P,Q)}{S_{\mathcal{Y}}(B)(Q)}$$

The spectra of functions

For any given function $f: \mathcal{X}^n \to \mathcal{Y}^m$, by considering the relation $\operatorname{rl}(f) \equiv \{(x^n, f(x^n)) | x^n \in \mathcal{X}^n\}$, we can define its *joint spectrum*, *forward conditional spectrum*, *backward conditional spectrum*, and *image spectrum* as

$$S_{\mathcal{X}\mathcal{Y}}(f) \equiv S_{\mathcal{X}\mathcal{Y}}(\mathrm{rl}(f))$$
$$S_{\mathcal{Y}|\mathcal{X}}(f) \equiv S_{\mathcal{Y}|\mathcal{X}}(\mathrm{rl}(f))$$
$$S_{\mathcal{X}|\mathcal{Y}}(f) \equiv S_{\mathcal{X}|\mathcal{Y}}(\mathrm{rl}(f))$$
$$S_{\mathcal{Y}}(f) \equiv S_{\mathcal{Y}}(\mathrm{rl}(f))$$

If f is a linear code, we further define its kernel spectrum as $S_{\mathcal{X}}(\ker f)$, where $\ker f \equiv \{x^n | f(x^n) = 0^m\}$. In this case, we also have

$$S_{\mathcal{Y}}(f) = S_{\mathcal{Y}}(f(\mathcal{X}^n))$$

since f is a homomorphism according to the definition of linear codes.

Please note that the linear code $f : \mathcal{X}^n \to \mathcal{Y}^m$ in our paper is a homomorphism between abellian groups, instead of a set of codewords. So traditional meaning of a linear code is only the image of a linear code in our paper.

Some new properties

Proposition 3.1: For any random function $F : \mathcal{X}^n \to \mathcal{Y}^m$ and any $x^n \in \mathcal{X}^n$, we have

$$\Pr\{(F \circ \Sigma_n)(x^n) \in \mathcal{T}_Q^m(\mathcal{Y})\} = E[S_{\mathcal{Y}|\mathcal{X}}(F)(Q|P_{x^n})].$$
(7)

Proposition 3.2: For any two random functions $F : \mathcal{X}^n \to \mathcal{Y}^m$ and $G : \mathcal{Y}^m \to \mathcal{Z}^l$, and any $O \in \mathcal{P}_n(\mathcal{X}), Q \in \mathcal{P}_l(\mathcal{Z})$, we have

$$E[S_{\mathcal{Z}|\mathcal{X}}(G \circ \Sigma_m \circ F)(Q|O)]$$

=
$$\sum_{P \in \mathcal{P}_m(\mathcal{Y})} E[S_{\mathcal{Y}|\mathcal{X}}(F)(P|O)]E[S_{\mathcal{Z}|\mathcal{Y}}(G)(Q|P)].$$

For comparison: $X \to Y \to Z, P_{Z|X}(z|x) = \sum P_{Y|X}(y|x)P_{Z|Y}(z|y).$

Generating function approach

For any set $A \subseteq \mathcal{X}^n$, we define the generating function $\mathcal{G}(A)$ of its spectrum to be

$$\mathcal{G}(A)(u) \equiv \sum_{P \in \mathcal{P}_n(\mathcal{X})} S_{\mathcal{X}}(A)(P)(u^{nP})_{\otimes} = \frac{1}{|A|} \sum_{x^n \in A} (u^{nP_{x^n}})_{\otimes},$$

and for any set $B \subseteq \mathcal{X}^n \times \mathcal{Y}^m$, we define the generating function of its joint spectrum as

$$\mathcal{G}(B)(u,v) \equiv \sum_{P \in \mathcal{P}_n(\mathcal{X}), Q \in \mathcal{P}_m(\mathcal{Y})} S_{\mathcal{X}\mathcal{Y}}(B)(P,Q)(u^{nP})_{\otimes}(v^{mQ})_{\otimes}$$

where $u \in \mathbb{C}^{\mathcal{X}}$, $v \in \mathbb{C}^{\mathcal{Y}}$, and

$$(u^{v})(a) \equiv u(a)^{v(a)} \quad \forall a \in \mathcal{X}, \qquad (u)_{\otimes} \equiv \prod_{a \in \mathcal{X}} u(a).$$

For any function $f: \mathcal{X}^n \to \mathcal{Y}^m$, we define its generating function as

$$\mathcal{G}(f) \equiv \mathcal{G}(\mathrm{rl}(f)).$$

Corollary 3.2: For any two functions $f_1 : \mathcal{X}^{n_1} \to \mathcal{Y}^{m_1}$ and $f_2 : \mathcal{X}^{n_2} \to \mathcal{Y}^{m_2}$, we have

$$\mathcal{G}(f_1 \odot f_2)(u, v) = \mathcal{G}(f_1)(u, v) \cdot \mathcal{G}(f_2)(u, v), \qquad (11)$$

where $f_1 \odot f_2$ is the map from $\mathcal{X}^{n_1+n_2}$ to $\mathcal{Y}^{m_1+m_2}$ defined by

$$(f_1 \odot f_2)(x^{n_1+n_2}) \triangleq f_1(x_{1\cdots n_1})f_2(x_{(n_1+1)\cdots(n_1+n_2)})$$

for all $x^{n_1+n_2} \in \mathcal{X}^{n_1+n_2}$.

General principles for constructing linear codes with good joint spectra

Criterion of good linear codes for JSCC

A sequence of δ -asymptotically good (random) linear codes $F_n: \mathcal{X}^n \to \mathcal{Y}^{m_n}$ for JSCC is a sequence of linear codes whose joint spectra satisfy

$$\limsup_{n \to \infty} \max_{\substack{P \in \mathcal{P}_n(\mathcal{X}) \setminus \{P_0n\}, \\ Q \in \mathcal{P}_{m_n}(\mathcal{Y})}} \frac{1}{n} \ln \frac{E[S_{\mathcal{XY}}(F_n)(P,Q)]}{S_{\mathcal{XY}}(\mathcal{X}^n \times \mathcal{Y}^{m_n})(P,Q)} \le \delta.$$

For comparison, a sequence of δ -asymptotically good (random) linear codes $F_n : \mathcal{X}^n \to \mathcal{Y}^{m_n}$ for channel coding is a sequence of linear codes whose image spectra satisfy

$$\limsup_{n \to \infty} \max_{Q \in \mathcal{P}_{m_n}(\mathcal{Y}) \setminus \{P_{0^{m_n}}\}} \frac{1}{m_n} \ln \frac{E[S_{\mathcal{Y}}(F_n(\mathcal{X}^n))(Q)]}{S_{\mathcal{Y}}(\mathcal{Y}^{m_n})(Q)} \leq \delta.$$

A sequence of asymptotically good linear codes for JSCC are subsets of asymptotically good linear codes for channel coding.

If a sequence of asymptotically good linear codes f_n for channel coding is given, can we find a sequence of asymptotically good linear codes g_n for JSCC such that $g_n(\mathcal{X}^n) = f_n(\mathcal{X}^n)$?

In other words (assuming that $\mathcal{X} = \mathcal{Y} = \mathbb{F}_q$), if a sequence of asymptotically good channel codes is given, can we choose a good sequence of generator matrices so that the linear codes are asymptotically good for JSCC?

Constructing good linear codes for JSCC based on good channel codes

Theorem 4.1: For any linear code $f : \mathbb{F}_q^n \to \mathcal{Y}^m$, there exists a linear code $g : \mathbb{F}_q^n \to \mathcal{Y}^m$ such that

$$g(\mathbb{F}_q^n) = f(\mathbb{F}_q^n)$$

and

$$S_{\mathcal{Y}|\mathbb{F}_q}(g)(Q|P) < \frac{S_{\mathcal{Y}}(f(\mathbb{F}_q^n))(Q)}{1 - q^{-1} - q^{-2}}$$
(12)

for all $P \in \mathcal{P}_n(\mathbb{F}_q) \setminus \{P_{0^n}\}, Q \in \mathcal{P}_m(\mathcal{Y}).$



Constructing good linear codes based on sparse matrices

Theorem 4.2: For a given sequence of sets $\{A_n \subseteq \mathcal{P}_{m_n}(\mathcal{X}) \setminus \{P_{0^{m_n}}\}\}_{n=1}^{\infty}$, if there exist two sequences of random linear codes $F_n : \mathcal{X}^n \to \mathcal{X}^{m_n}$ and $G_n : \mathcal{X}^{m_n} \to \mathcal{X}^{l_n}$ satisfying

$$F_n(\mathcal{X}^n \setminus \{0^n\}) \subseteq \bigcup_{P \in A_n} \mathcal{T}_P^{m_n}(\mathcal{X})$$
(16)

and

$$\limsup_{n \to \infty} \max_{P \in A_n, Q \in \mathcal{P}_{l_n}(\mathcal{X})} \frac{1}{n} \ln \frac{E[S_{\mathcal{X}|\mathcal{X}}(G_n)(Q|P)]}{S_{\mathcal{X}}(\mathcal{X}^{l_n})(Q)} \le \delta \quad (17)$$

respectively, where $\delta \geq 0$, then we have

$$\lim_{n \to \infty} \sup_{O \in \mathcal{P}_n(\mathcal{X}) \setminus \{P_{0^n}\}, Q \in \mathcal{P}_{l_n}(\mathcal{X})} \frac{1}{n} \ln \frac{E[S_{\mathcal{X}|\mathcal{X}}(G_n \circ \Sigma_{m_n} \circ F_n)(Q|O)]}{S_{\mathcal{X}}(\mathcal{X}^{l_n})(Q)} \leq \delta.$$

A serial concatenation scheme



$$\limsup_{n \to \infty} \max_{P \in A_n, Q \in \mathcal{P}_{l_n}(\mathcal{X})} \frac{1}{n} \ln \frac{E[S_{\mathcal{X}|\mathcal{X}}(G_n)(Q|P)]}{S_{\mathcal{X}}(\mathcal{X}^{l_n})(Q)} \le \delta$$
$$\limsup_{n \to \infty} \max_{P \in \mathcal{P}_{m_n}(\mathcal{X}) \setminus P_{0^{m_n}}, Q \in \mathcal{P}_{l_n}(\mathcal{X})} \frac{1}{n} \ln \frac{E[S_{\mathcal{X}|\mathcal{X}}(G_n)(Q|P)]}{S_{\mathcal{X}}(\mathcal{X}^{l_n})(Q)} \le \delta$$

The Spectra of LDGM codes

Low-density generator matrix codes

A regular LDGM code: $F_{n,c,d}^{\text{LD}} \equiv (\odot_{i=1}^{m} F_d^{\text{CHK}}) \circ \Sigma_{cn} \circ (\odot_{i=1}^{n} f_c^{\text{REP}})$ where nc = md, and f_c^{REP} is a single symbol repetition code $f_c^{\text{REP}} : \mathbb{F}_q \to \mathbb{F}_q^c$ defined by $f_{c}^{\text{REP}}(x) \equiv xx \cdots x \quad \forall x \in \mathbb{F}_{q},$ and $\odot_{i=1}^{m} F_d^{\text{CHK}}$ denotes a parallel concatenation of m independent copies of the random single symbol check code $F_d^{\text{CHK}} : \mathbb{F}_q^d \to \mathbb{F}_q$ defined by $F_d^{\text{CHK}}(x^d) \equiv \sum_{i=1}^d C_i x_i \quad \forall x^d \in \mathbb{F}_q^d$ where C_i $(i = 1, 2, \dots, d)$ denotes an independent uniform random variable on the set $\mathbb{F}_q \setminus \{0\}$.

The bipartite graph



 $\Rightarrow (\odot_{i=1}^{n} f_{c}^{\text{REP}}) \rightarrow \Sigma_{cn} \rightarrow (\odot_{i=1}^{m} F_{d}^{\text{CHK}}) \Rightarrow$

Th

Theorem 5.1:

$$\frac{1}{n}\ln\alpha(F_{n,c,d}^{\mathrm{LD}})(P,Q) \le \frac{c}{d}\delta_d(P(0),Q(0)) + O\left(\frac{\ln n}{n}\right).$$
(29)

where δ_d is defined by (28). Let

$$A_n(\gamma) \stackrel{\triangle}{=} \{ P \in \mathcal{P}_n(\mathbb{F}_q) | 1 - P(0) > \gamma \}, \tag{30}$$

where $0 < \gamma < 1$. Then, when q > 2, for any $0 < \gamma < 1$ and any $\delta > 0$, there exits a positive integer $d_0 = d_0(\gamma, \delta)$ such that

$$\limsup_{n \to \infty} \max_{P \in A_n(\gamma), Q \in \mathcal{P}_m(\mathbb{F}_q)} \frac{1}{n} \ln \alpha(F_{n,c,d}^{\mathrm{LD}})(P,Q) \le \delta \quad (31)$$

for all integers $d \ge d_0$.

An explicit construction of good linear codes for JSCC



An extension of this conference paper ("Constructing Linear codes with Good Spectra") is now in preparation, to be submitted to IEEE TIT.



Homepage: http://www.yangst.codlab.net